

NoiseSensor LITE with 4-20mA Current Loop Output



Features

- Type 2 Noise Measurement
- 4-20mA Current Loop Output
- Hazardous environments
- Easy installation (no controls or settings)
- Measures 'A' weighted sound level - dB(A)

Applications

- Integrate with control system (e.g. SCADA, DCS)
- Indoor or outdoor installation
- Hazardous and potentially explosive atmospheres
- Boundary, construction or industrial noise

Overview

The MK440 NoiseSensorLITE is a trimmed down version of the MK427 NoiseSensor noise monitor. Meeting the sound level meter standards to Type 2, it is intended for monitoring around industrial and construction sites, although there are many other noise monitoring applications for which it fits the bill.

The NoiseSensorLITE converts the 'A' weighted sound level into a 4-20mA current loop output, which is ideal for linking to existing process control and monitoring systems, such as SCADA or DCS.

As the microphone and noise processing technology is all contained within the MK440 the installation process is simple. There is no configuration needed, just electrical connections for power and for the current loop output.



NoiseSensor LITE with 4-20mA Current Loop Output

Specifications

Technical specifications for the MK440 NoiseSensorLITE noise monitor with 4-20mA current loop output.

Output Type	Sound level in 4-20mA loop
Frequency Weighting	'A' (factory option for 'C' or 'Z' weighting)
Time Weighting	Fast (factory option for Slow response)
Measurement Range	34 to 104 dB (factory options: 24-94 dB, 44-114 dB, 54-124 dB, 64-134 dB)
Current Loop Out	I _{out} = 0.1 mA/dB
Weight	1.8 kg
Power Supply Current	12 to 24 VDC 70 mA
Cable Entry	1/2" NPT or M20 Gland
Operating Temp.	-10°C to +50°C
Protection	Enclosure: IP65, Microphone: IP54

Head Office

NoiseMeters Inc
3233 Coolidge Hwy
Berkley
MI 48072
USA

Telephone **888 206 4377**
Fax **888 584 2230**

Email: **info@noisemeters.com**
Support: **support@noisemeters.com**

Web Sites

Main site:
<https://www.noisemeters.com>

Product shortcut:
<https://www.noisemeters.com/p/mk440/>

Tech Support:
<https://support.noisemeters.com>